

# ACCESSORIES

## Low Pressure Fuel Solenoid Kit

- Positive flow shut off valve
- Allows generator to run unattended



## Maintenance Kit

- NAPA Premium 10W-30 oil
- Sta-bil fuel stabilizer
- Bosch Platinum spark plug
- NAPA air filter



## Two Wheel Dolly Kit

- For 6kW and 9kW
- 10" diameter no-flat tires
- Fold down handle
- 12kW comes standard with 4-wheel dolly kit

## Battery

- Interstate 300 CCA
- 6-month free replacement



## WINCO Emergency Transfer Switch

- Allows your portable generator to be quickly and safely connected to a building electrical panel for backup service during a power outage
- Outdoor enclosure
- Square D circuit breaker load center



## Battery Charger

- Helps keep the battery charged



## Generator Cover

- Made of heavy canvas
- Weather resistant
- Large cover for 12kW
- Small cover for 6kW and 9kW



# GeneratorJoe®

## GeneratorJoe®

4723 Muirfield Court  
 Santa Rosa, CA 95405  
 Phone: 707 542-2224  
 Fax: 707 542-2227

Email: [sales@generatorjoe.net](mailto:sales@generatorjoe.net)  
 Web: [www.generatorjoe.NET](http://www.generatorjoe.NET)

# WINCO®

## MULTI-FUEL GENERATORS



# HOME POWER<sup>®</sup>

The convenience of a portable generator with the versatility of multiple fuel sources. No portable unit is better prepared for when life happens.



HPS9000VE

## MAINTAINS ENGINE WARRANTY

WINCO uses premium Honda GX and Briggs & Stratton Vanguard engines. These engines have gone through an extensive application review which allows them to maintain a full engine warranty. Other after-market fuel conversion kits will void the manufacturer's warranty and are not EPA compliant.



MODEL	HPS6000HE*	HPS9000VE	HPS12000HE
-------	------------	-----------	------------

### ELECTRICAL SPECIFICATIONS

Max Rating (1)	6000 watts	9000 watts	12000 watts
Cont. Rating Gasoline	5500 watts	8000 watts	10800 watts
Cont. Rating LP	N/A	7200 watts	9720 watts
Cont. Rating NG	4400 watts	6400 watts	8640 watts
Voltage	120/240	120/240	120/240
Cont. Amps (1)	45.8/22.9	66.7/33.3	90/45
Motor Starting (1)(2)	2 hp	4 hp	5 hp

### ENGINE DATA

Make/Model	Honda GX340	B&S Vanguard	Honda GX630
Displacement	389cc	480cc	688cc
Starting System (3)	Electric/Recoil	Electric/Recoil	Electric
Fuel Tank Capacity	7 gal	7 gal	15 gal
Low Oil Protection	Standard	Standard	Standard
dba Rating @ 7 Meters	72	77	78

### FUEL CONSUMPTION

Gasoline	1.0 gal/hr	1.3 gal/hr	1.67 gal/hr
LP Vapor	N/A	1.9 gal/hr	2.2 gal/hr
Natural Gas	160 ft <sup>3</sup> /hr	180 ft <sup>3</sup> /hr	200 ft <sup>3</sup> /hr

### RECEPTACLES

120V NEMA 5-20R	2-20 amp	4-20 amp	4-20 amp (GFCI)
120/240 Twist-lock NEMA L14-30R	1-30 amp	1-30 amp	1-30 amp
120/240V Straight Blade NEMA 14-60R	-	-	1-60 amp

### GENERAL INFORMATION

Dimensions(in)(LxWxH)	32.75x 22.5x 22	32.75x 22.5x 22	44.7x 36x 33 (4)
Shipping Weight	224 lbs	267 lbs	460 lbs
Engine/Generator Warranty (5)	3 yr/2 yr	3 yr/2 yr	3 yr/2 yr

NOTE: (1) Based on gasoline fuel, derate 10% for LP and 20% for NG (2) Code G capacitor start motor (3) Battery NOT included, see individual spec sheets for battery requirements (4) HPS12000HE dimensions include installed wheel kit (5) Prime Power Warranty-120 days. Engine warranty administered by engine manufacturer. Contact your local Honda or B&S service center for warranty assistance. WINCO Inc. can assist in locating appropriate engine warranty support. \*HPS6000HE is not certified for LP gas use.

# GeneratorJoe<sup>®</sup>

## CONFIDENCE

Reliable components with exceptional engineering ensures your unit will work whenever you need it. With Total Harmonic Distortion (THD) of less than 6%, your generator is safe to run sensitive household electronics.



HPS6000HE

## EXPERIENCE

1987. That makes these multi-fuel units the longest Multi-fuel generators have been built by WINCO since lasting on the market.



HPS12000HE

## GeneratorJoe<sup>®</sup>

4723 Muirfield Court  
Santa Rosa, CA 95405

Phone: 707 542-2224

Fax: 707 542-2227

Email: [sales@generatorjoe.Net](mailto:sales@generatorjoe.Net)

Web: [www.generatorjoe.NET](http://www.generatorjoe.NET)