

UL 1008 Withstand & Closing Ratings

When used with Specific Coordinated Breakers!!

Maximum Circuit Amps at 480 VAC

Includes ZTG 260A Upgrade (in process)

GE Zenith Controls, Chicago, IL

17 June 2003, Compiled by Steve Mecker

Amps	ZTS		ZTSD		ZTSCT		ZBTS		ZBTSD		ZBTSCT		ZTG		ZTGD		ZTX		Amps	
40	F17	30,000	F14B	50,000	no F14		#N/A		#N/A		no F14		F17	30,000	F14B	50,000	30,000		40	
80		30,000		50,000	no F14		#N/A		#N/A		no F14			30,000		50,000	30,000		80	
100		30,000		50,000	no F14		#N/A		50,000		no F14			30,000		50,000	30,000		100	
150		30,000		50,000	no F14		#N/A		50,000		no F14			30,000		50,000	30,000		150	
200	#N/A		#N/A	#N/A	#N/A		#N/A		#N/A		#N/A		#N/A	#N/A	#N/A		30,000		200	
225	F14	50,000	F14B	50,000	no F14		F14C	50,000	F14B/C	50,000	no F14		F17	30,000	F14B	50,000	30,000		225	
260		50,000		50,000	no F14			50,000		50,000	no F14			35,000		50,000	#N/A		260	
300		#N/A		#N/A	#N/A			#N/A		#N/A	#N/A			#N/A		#N/A	#N/A		50,000	300
400		50,000		50,000	no F14			50,000		50,000	no F14			F14		50,000	50,000	50,000		400
600	ZTS2	65,000	ZTS2	65,000	ZTS2	65,000	ZTS2	65,000	ZTS2	65,000	ZTS2	65,000	F14	50,000	ZTS2	65,000	600		600	
800		65,000		65,000		65,000		85,000		85,000		85,000		85,000		85,000	85,000	65,000	65,000	800
1,000	ZTS	85,000	ZTS	85,000	ZTS	85,000	ZBTS	85,000	ZBTS	85,000	ZBTS	85,000	ZTS	85,000	ZTS	85,000	1,000		1,000	
1,200		85,000		85,000		85,000		85,000		85,000		85,000		85,000		85,000	85,000	85,000	85,000	1,200
1,600	ZTS	100,000	ZTS	100,000	ZTS	100,000	ZBTS	100,000	ZBTS	100,000	ZBTS	100,000	ZTS	100,000	ZTS	100,000	#N/A		1,600	
2,000		100,000		100,000		100,000		100,000		100,000		100,000		100,000		100,000	100,000	100,000	100,000	2,000
2,600		100,000		100,000		100,000		100,000		100,000		100,000		100,000		100,000	100,000	100,000	100,000	2,600
3,000		100,000		100,000		100,000		100,000		100,000		100,000		100,000		100,000	100,000	100,000	100,000	3,000
4,000	100,000	100,000	#N/A		#N/A		4,000		#N/A		#N/A		4,000		4,000		4,000			

UL references:

- ZTS -- E23911, Vol. 4, Sec. 10 (1,000-1,200A), Sec. 12 (1,600-2,000A), Sec. 11 (2,600-3,000A), Sec. 15 (4,000A).
- ZTS2 -- E23911, Vol. 4, Sec. 9 (600- 800A).
- ZBTS -- E67544, Vol. 1, Sec. 5 (800-1,200A), Sec. 8 (1,600-3,000A), Sec. 9 (4,000A)

NOTE: THIS IS A PARTIAL EXCERPT FROM TECHNICAL BULLETIN TB1102. FOR MORE INFORMATION ON SPECIFIC COORDINATED BREAKER USE, PLEASE REQUEST THE COMPLETE DOCUMENT TB-1102



GeneratorJoe

4016 Quartz Drive
 Santa Rosa, CA 95405
 Phone: 707 539-9003
 Fax: 707 539-5212
 Email: sales@generatorjoe.NET
 Web www.generatorjoe.NET