

FOR INDIVIDUAL GEN-SET MODEL TYPES SEE BROADCAST LITERATURE.

ENGINE TYPE: MITSUBISHI S3L2
 ALTERNATOR: BCI 164 B/C
 (BCI 164 B ILLUSTRATED)

USEABLE FUEL CAPACITY: 52L

SHIPPING WEIGHT
 (WITH OIL): Kg - Kg

WET WEIGHT
 50/50 GLYCOL & FUEL: Kg - Kg

OIL CAPACITY: 3.7 LITRES
 COOLING CAPACITY: LITRES

GENERATOR IS TO BE PLACED ON A FLAT FLOOR OR CONCRETE BASE.

PLEASE NOTE WEIGHTS MAY VARY DEPENDING ON ALTERNATOR COMBINATION.



GeneratorJoe

4016 Quartz Drive
 Santa Rosa, CA 95405
 Phone: 707 539-9003
 Fax: 707 539-5212
 Email: sales@generatorjoe.NET
 Web www.generatorjoe.NET

ISS	ALTERATIONS	DATE

NOTES

TOLERANCES:
 BETWEEN HOLE CENTRES & HOLE CENTRE TO EDGE (ON FLAT) ± 0.2
 HOLE CENTRES TO BEND AND EDGES TO BEND ± 0.5
 ACROSS EACH BEND ± 0.5
 FABRICATION ± 1.0
 HOLE DIAMETERS AND SLOT WIDTHS +0.1, -0.0
 ANGULAR ± 0.5°

THIRD ANGLE PROJECTION
 DO NOT SCALE, IF IN DOUBT ASK

DISTRIBUTION

MASTER	FABRICATOR
--------	------------

TITLE:	S3 L2 GENERAL ARRANGEMENT		
CLIENT:			
SITE:			
W.O. No.:	ENGINEER:	P.RUTTER	
TYPE:	MITSUBISHI	CHECKED:	
SCALE:	NTS	DATE:	
TOTAL No. OF SHEETS:			1

DRAWING NO.	ISSUE
MGA001	A

BROADCAST

